



EC Series

Indoor Industrial Application Emergency



PROJECT: _____
FIXTURE TYPE: _____
LOCATION: _____
CONTACT/PHONE: _____




SPECIFICATIONS: INTERNAL

The EC is configured with 120/277V input and a high-efficiency two stage charger providing precise float voltage control with low voltage disconnect protection. All components used in the circuitry are temperature compensated. Charger status is easily determined via a dual diagnostic LED display. Standard features include low voltage disconnect, AC lockout and brownout protection.

SPECIFICATIONS: EXTERNAL

The EC is constructed with a 20 gauge steel cabinet for lower wattages and 18 gauge steel for higher capacities. Terminal connectors allow for larger gauge wires to be connected for remote loads. The universal mounting pattern with key hole slots stamped into the back of the unit allows for direct mounting to various conduit boxes. Stamped conduit knockouts are supplied standard on all EC units optimize AC power source options.

DIMENSIONS



Unit Size	Steel (ga)	A	B	C
(6V 18-22W)	20	12 ^{1/4"} (311mm)	5" (127mm)	3" (76mm)
(6V/12V 36W)	20	10" (254mm)	9" (229mm)	3 ^{1/4"} (83mm)
(6V 42-90W) (12V 42-60W)	18	13 ^{1/2"} (343mm)	10 ^{1/8"} (257mm)	4 ^{1/4"} (108mm)
(12V 90W)	18	13" (330mm)	10 ^{1/8"} (257mm)	8 ^{1/2"} (216mm)

NOTE: Cabinet size may vary based on product configuration. Dimension D in drawing above will vary based on heads supplied.



ORDERING INFORMATION

Series	Operation	Pb-A (Capacity)	Ni-Cd ¹ (Capacity)	Emergency Heads	Lamps	Options
EC	6 (6V)	12 (6V)	22 (6V)	0 (no heads)	See Lamp Selection	AM (ammeter)
	12 (12V)	18 (6V)	42 (6V, 12V)	1LR (Single PAR36)	on the next page	SD (self diagnostic)
		27 (6V, 12V)	90 (6V, 12V)	2LR (Double PAR36)		BZ (buzzer)
		36 (6V, 12V)		1MRB (Single MR16 bullet style)		CC (custom color- specify)
		54 (6V)		2MRB (Double, MR16 bullet style)		CS120 (cord set, 120V only)
		60 (6V, 12V)		1SRE (Single LED module)		FAI ² (fire alarm interface)
				2SRE (Double LED module)		IRT ³ (infrared testing)
				1MEGASQ (Single, MEGA)		NC ¹ (Ni-Cd)
				2MEGASQ (Double, MEGA)		SM (side mounted heads)
						TP (tamper proof screws)
						TD ⁴ (time delay - specify 5, 10, 15 min)
						VM (voltmeter)

NOTE 1: For nickel-cadmium battery, select NC from options and capacity from Ni-Cd column

NOTE 2: Specify type of fire alarm signal: normally open, normally closed or 6, 12, 24VDC (specify voltage used)

NOTE 3: HHC (hand held controller for IRT) should be ordered separately

NOTE 4: Must specify input voltage and time delay (10 min standard)

EXAMPLE: EC-6-18-2LR9W-SD



EC Series

Indoor Industrial Application Emergency



PROJECT:

FIXTURE TYPE:

LOCATION:

CONTACT/PHONE:

EMERGENCY HEADS

The EC is supplied standard with two (2) top mounted PAR36 style heads with 9W incandescent lamps. LED lamp options include sealed beam LED LR style lamp heads, MRB style heads with LED MR16 lamps, SRE LED heads or MEGSQ square LED lamp heads. Lamp heads can be mounted either on the top or on the sides of the unit allowing for up to four (4) heads to be mounted on the largest units (2 top, 2 side or 3 on top). The lamp head styles are constructed of high impact thermoplastic in a color matching the finish of the cabinet (white is standard). Both head types feature a unique twist locking collar that securely holds the lens and facilitates quick and easy re-lamping.

SPECIFICATIONS: ELECTRICAL

BATTERY: The EC is designed with a maintenance free, sealed valve regulated lead acid battery or Ni-Cd battery that provides a minimum emergency duration of 90 minutes (for the listed rating). Recharge time of the battery is 24 hours. An optional Nickel-Cadmium battery is available.

SPECIFICATIONS: MECHANICAL

Remote lamp loads are connected to the emergency power supply with sturdy terminal connectors. These connectors allow for a large gauge of wire to be used increasing the flexibility of installation. The EC is supplied standard in a durable white powder coat, baked finish. Other colors are available, including custom color matching, please specify.

SELF-DIAGNOSTIC

The Mule self-diagnostic system (optional) performs one 5 minute discharge test monthly. Every 6 months two 90 minute discharge tests are performed. This tests both full battery capacity and recharge capability, as required by the fire code. The information is communicated simply and intuitively to maintenance personnel via a single multi-color LED. The Mule self-diagnostic system also includes 0, 5, 10 or 20 minute time delay function to allow HID lighting to restrike. IRT one button press tests unit for 90 minutes per code.

WARRANTY

The EC comes with a 3-year factory warranty. Lamps are not covered under the warranty. Deliberate damage, misuse, improper installation effectively cancel the warranty.

LAMP SELECTION

	6V	12V
Incandescent	7.2, 9W	9, 12, 18W
Quartz	12W	12, 20W
MR16LED (MRB)	5, 7W	2, 5, 7W
MEGSQ	N/A	5, 9, 14, 30W
Sealed Beam LED Module SRE (PAR36 Only)	N/A	6W

MODEL RATING GUIDE PB-A (CAPACITY)

Model	Input Voltage	Wattage Rating 90 Minutes
EC-6-12	6	12
EC-6-18	6	18
EC-6-27	6	27
EC-6-36	6	36
EC-6-54	6	54
EC-6-60	6	60
EC-12-27	12	27
EC-12-36	12	36
EC-12-60	12	60

MODEL RATING GUIDE NI-CD (CAPACITY)

Model	Input Voltage	Wattage Rating 90 Minutes
EC-6-22	6	22
EC-6-42	6	42
EC-6-90	6	90
EC-12-42	12	42
EC-12-90	12	90