



LX Series

Industrial Application Emergency



PROJECT: _____
 FIXTURE TYPE: _____
 LOCATION: _____
 CONTACT/PHONE: _____




SPECIFICATIONS: INTERNAL

The LX is configured with 120/277V input and a high- efficiency two stage charger providing precise float voltage control with low voltage disconnect protection. All components used in the circuitry are temperature compensated. Charger status is easily determined via a dual diagnostic LED display. Standard features include low voltage disconnect, AC lockout and brownout protection.

SPECIFICATIONS: EXTERNAL

The LX cabinet is constructed with 20 gauge steel for models below 42W and 18 gauge for > 42W. Terminal connectors allow for larger gauge wires to be connected for remote loads. A universal knockout pattern with keyhole slots on the back of the unit optimizes mounting flexibility. Stamped conduit knockouts provide the LX with the widest range of options for AC power source connection.

DIMENSIONS



Unit Size	A	B	C
(6V 36W) (12V 36W)	10" (254mm)	9" (229mm)	3 1/4" (82mm)
(6V 42W-90W) (12V 60-90W)	13 1/2" (343mm)	10 1/8" (257mm)	4 1/4" (108mm)

*NOTE: Cabinet size may vary based on product configuration. Dimension D in drawing above will vary based on heads supplied.



ORDERING INFORMATION

Series	Operation	Pb-A (Capacity)	Ni-Cd ³ (Capacity)	Emergency Heads	Lamps	Options
LX	6V	36 (6V,12V)	42 (6V, 12V)	2LR (double PAR36)	See Lamp Selection	ACTB (terminal block AC)
	12V	60 (6V, 12V)	90 (6V, 12V)	1LR (single PAR36)	on the next page	AM (ammeter)
	24V				2BTMR(double,MR16)	SD (self diagnostic)
					1BTMR(single,MR16)	B (black finish)
				2SRE (double LED module)		BZ (buzzer)
				1SRE (single LED module)		CC (custom color- specify)
				0 (no heads)		CS120 (cord set, 120V only)
						DCTB (terminal block DC)
						FAI ¹ (fire alarm interface)
						IRT ² (infrared testing)
						NC ³ (Ni-Cd)
						TD ⁴ (time delay - specify 5, 10, 15 min)
						TP (tamper proof screws)
						VM (voltmeter)

NOTE 1: Specify open/closed/6-24VDC.
 NOTE 2: HHC (controller for IRT) should be ordered separately.
 NOTE 3: Must select NC from options and indicate wattage/voltage from Ni-Cd column.
 NOTE 4: Must specify at time of order. Specify voltage
 ** Aluminum heads not rated for wet location.

EXAMPLE: LX-6-36-2LR-9W



LX Series

Industrial Application Emergency



PROJECT: _____
 FIXTURE TYPE: _____
 LOCATION: _____
 CONTACT/PHONE: _____

EMERGENCY HEADS

The LX is supplied with two (2) top mounted 9W incandescent LR style heads. LED lamp head options include: BTMR steel heads utilizing LED MR16 lamps and SRE thermoplastic LED module heads. Lamp heads can be mounted either on the top or on the sides of the unit. The LR lamp heads are constructed of high impact thermoplastic in a color matching the finish of the cabinet (white is standard). BTMR and SRE lamp heads are available in white and black finish only. Heads feature a unique twist locking collar that securely holds the lens and facilitates quick and easy re-lamping.

SPECIFICATIONS: ELECTRICAL

BATTERY: The LX is designed with a maintenance free, sealed valve regulated lead acid battery that provides a minimum emergency duration of 90 minutes (for the listed rating). Recharge time of the battery is 24 hours. An optional Nickel-Cadmium battery is available. The operating temperature is 50°F to 104°F (10°C to 40°C).

SPECIFICATIONS: MECHANICAL

The LX is supplied standard in a durable white powder coat, baked finish. Other colors are available, including custom color matching, please specify. Remote lamp loads are connected to the emergency power supply with sturdy terminal connectors. These connectors allow for a large gauge of wire to be used increasing the flexibility of installation. Compatible with BTMR and MEGA remotes. Consult factory for additional options.

SELF-DIAGNOSTIC

The Mule Self Diagnostic (optional) performs one 5 minute discharge test monthly. Every 6 months two 90 minute discharge tests are performed. This tests both full battery capacity and recharge capability, as required by the fire code. The information is communicated simply and intuitively to maintenance personnel via a single multi-color LED. The Mule Self Diagnostic also includes 0, 5, 10 or 20 minute time delay function to allow HID lighting to re-strike. IRT one button press tests unit for 90 minutes per code.

WARRANTY

The LX comes with a 3-year factory warranty. Lamps are not covered under the warranty. Deliberate damage, misuse, improper installation effectively cancel the warranty.

LAMP SELECTION

	6V	12V	24V
Incandescent	9W	9, 12, 18W	9, 18W
MR16 LED (BTMR)	5, 7W	2, 5, 7W	N/A
LED MODULE (SRE)	3,4W	3,4W	N/A

MODEL RATING GUIDE PB-A (CAPACITY)

Model	Input Voltage	Wattage Rating 90 Minutes
LX-6-36	6	36
LX-6-60	6	60
LX-6-72	6	72
LX-12-27	12	27
LX-12-36	12	36
LX-12-60	12	60

MODEL RATING GUIDE NI-CD (CAPACITY)

Model	Input Voltage	Wattage Rating 90 Minutes
LX-6-42	6	42
LX-6-90	6	90
LX-12-42	12	42
LX-12-90	12	90